



## ZS5062

6 Ch Speaker Zone Selector

## ZS5122

12 Ch Speaker Zone Selector

**ZS5062** and **ZS5122** have been improved in its individual zone rating with 1000W 100V line to meet the demand to increase zone loading in today's installations. They differ from other zone selector, i.e. they have fall safe feature which would ensure zone is always connected for paging if the unit itself failed. RS485 port is available for remote triggering and monitoring via PMX software.

- **1000W 100V** per zone rating
- **Zone monitoring** via PMX III software
- Local paging **override** bypassing BGM
- **Flexible** amplifier to zone configuration
- **Fall safe** zone trigger during power or unit failure
- **Remote zone triggering** via analogue and RS485 data
- Available in 6 and 12 zones ; expandable to **248 zones**

ZS5062



ZS5122



## Technical Specifications

	ZS5062	ZS5122
Operating voltage	24V DC via PS9400	
Power consumption (idle)	3.29W	6.25W
Power consumption (All Call)	0.72W	0.96W
Current consumption (idle)	0.14A	0.26A
Current consumption (All Call)	0.03A	0.04A
Max load / channel	1000W 100V Line	
Number of zones	6	12
Amplifier inputs	6	12
Zone selection	Front panel switch & remote (zone & all call)	
Max cascade	16 units	
Remote triggering	-ve triggered (common ground)	
Indicators	Individual zone switch, all call, and priority	
Data communications	RS485: 19.2 kbps baud rate	
Switching mode	Individual, All Call Local zone bypassed when remote trigger is activated	
Operating temperature	-10° ~ 60°C	
Dimensions (W x H x D)	482 x 44 x 180 mm (1hu)	
Weight	1.95 kg	2.10 kg

## Packing Information

Carton size : 550 (L) x 295 (W) x 95 (H) mm

Gross weight : ZS5062 - 2.55 kg  
: ZS5122 - 2.70 kg

1 unit per carton

