

# AMP MONITOR PANEL / SOURCE SELECTOR

## AM4120 12 Ch Amplifier Monitor Panel




AM4120 shall be used to monitor amplifier outputs of 70 / 100V line at the rack which is equipped with level meter, amplifier output LED and speaker for audio monitoring. It can also be used as a tool to calibrate sound output level of each amplifier from the rack.

### Features

- 12 inputs for 70 / 100V line amplifier outputs
- Dual mode monitoring with continuous signal indicator
- Audio monitoring with volume control

### Technical Specifications

Operating voltage	24V DC via PS9400 PSU
Power consumption	50 mW
Amplifier inputs	12 : 70 / 100V line
Monitoring mode	Audio : 1W speaker with 5 presets Visual : segment LED level meter LED for all channels
Dimensions (W x H x D)	482 x 44 x 180 mm
Weight	2.15 kg



Rear View:

Inputs from power amplifiers



#### Packing information

Carton size : 555 (L) x 295 (W) x 95 (H) mm  
Gross weight : 2.80 kg  
1 unit per carton

## SS6401 Audio Source Selector




SS6401 has 4 BGM source inputs via RCA jack with mono output suitable for PA system. Input channels of different BGM output sources with different line level has been equalized to the same level at output to avoid the trouble of adjusting the mixer gain whenever a source is changed.

### Features

- 4 input BGM sources
- Input level balancing for constant output

### Technical Specifications

Operating voltage	24V DC via PS9400 PSU
Power consumption	3.6 W ; 0.15 A
Input connections	RCA mono
Input level / impedance	CD : 2V / 47 k Ohm Tuner : 600 mV / 10 k Ohm Cass : 500 mV / 10 k Ohm Aux : 1.25 V / 20 k Ohm
Output connection	RCA mono ; 1V 600 Ohm
Gain / attenuation	CD : -6 dB, Tuner : 4 dB Cass : 6 dB, Aux : -2 dB
Selection	Daisy chain
Dimensions (W x H x D)	482 x 44 x 180 mm
Weight	1.8 kg



Rear View:

Inputs for audio sources

RCA output

#### Packing information

Carton size : 555 (L) x 295 (W) x 95 (H) mm  
Gross weight : 2.50 kg  
1 unit per carton

